
energøstack

Homebase

EWG6-C

The EWG6-C Homebase is the heart of Energostack installation. The Homebase collects data and controls the sensors via a wireless connection in a particular location.

It is compatible with all unpaired sensors (indicated in the required accessories section).





Technical data

Part	gateway
Physical dimensions	$110 \times 80 \times 26$ mm (without antenna)
Weight	128 g
Material	ABS plastic or aluminium
Protection	IP20
Working conditions	from 0 °C to + 60 °C, < 80 % RH (non-condensing)
Interface	USB Power connector, LAN connector, Programming port
Antenna	external, fixed
Interaction	display, LED signalisation
Power supply	external - 5V DC (USB) adapter, $1 \times 230V$ AC
Connectivity	433MHz Radio (Chirp protocol), Ethernet
Radio transmition mode	UNIQ Broadcast, IDN Broadcast
Max . power consumption	2 W